

## ZUNZUN BLOCK

TAITO 1979

pinout as tested on working board

### G connector

-----				
+5V	A	1	+5v	
+5V	B	2	+5v	
+5V	C	3	+5v	
+5V	D	4	+5v	
	E	5		
2P pot input	F	6	1P pot input	
2P serv	H	7	1P serv	
KEY	J	8	KEY	
Coin2	K	9	Coin 1	
2p Start	L	10	1P Start	
	M	11		
	N	12		
	P	13		
	R	14	Composite Video	
	S	15		
GND	T	16	GND	
GND	U	17	GND	
GND	V	18	GND	
-----				

Use 5k potentiometer between GND and +5v, connect wiper to pin 6 or F  
2P controls only used in cocktail mode. (put big switch 3 on)

### N connector (BOTH SIDES EQUAL)

-----		
	1	GND
	2	GND
	3	GND
	4	GND
	5	AUDIO+
	6	
	7	GND
	8	GND
	9	GND
	10	GND
	11	KEY
	12	
	13	+12V
	14	+12V
	15	+5V
	16	+5V
	17	+5V
	18	+5V
-----		

Use GND as AUDIO-